

OPEN Industry Standard, Flexible Architecture

GREEN Less Heat, Less Power Consumption

STABLE Robust Design, Quality Parts

Stable and
Reliable Solution

Server/Workstation
Motherboard

2U12L2S-SIENA

User Manual

English



Version 1.00

Published Jan. 2025

Copyright©2025 ASRock Rack Inc. All rights reserved.

Copyright Notice:

No part of this documentation may be reproduced, transcribed, transmitted, or translated in any language, in any form or by any means, except duplication of documentation by the purchaser for backup purpose, without written consent of ASRock Rack Inc.

Products and corporate names appearing in this documentation may or may not be registered trademarks or copyrights of their respective companies, and are used only for identification or explanation and to the owners' benefit, without intent to infringe.

Disclaimer:

Specifications and information contained in this documentation are furnished for informational use only and subject to change without notice, and should not be constructed as a commitment by ASRock Rack. ASRock Rack assumes no responsibility for any errors or omissions that may appear in this documentation.

With respect to the contents of this documentation, ASRock Rack does not provide warranty of any kind, either expressed or implied, including but not limited to the implied warranties or conditions of merchantability or fitness for a particular purpose.

In no event shall ASRock Rack, its directors, officers, employees, or agents be liable for any indirect, special, incidental, or consequential damages (including damages for loss of profits, loss of business, loss of data, interruption of business and the like), even if ASRock Rack has been advised of the possibility of such damages arising from any defect or error in the documentation or product.



This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

CALIFORNIA, USA ONLY

The Lithium battery adopted on this motherboard contains Perchlorate, a toxic substance controlled in Perchlorate Best Management Practices (BMP) regulations passed by the California Legislature. When you discard the Lithium battery in California, USA, please follow the related regulations in advance.

“Perchlorate Material-special handling may apply, see www.dtsc.ca.gov/hazardouswaste/perchlorate”

Setting up the Server in a Restricted Access Location/Restricted Access Area

- Access can only be gained by service persons or by users who have been instructed about the reasons for the restrictions applied to the location and about any precautions that shall be taken.
- Access is through the use of a tool or lock and key, or other means of security, and is controlled by the authority responsible for the location.
- Leave enough clearance (25 inches in the front and 30 inches in the back of the rack) to allow the front door to be opened completely and to allow for sufficient airflow.
- This product is for installation merely in a Restricted Access Location.
- This product is not suitable for use with visual display work place devices according to §2 of the the German Ordinance for Work with Visual Display Units.
- Only skilled person and Instructed person can remove the chassis covers to access the inside of the system.

ASRock Rack's Website: www.ASRockRack.com

Replaceable Batteries

CAUTION

**RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE.
DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS**

Warning

When removal of the chassis lid required for servicing:

- Turn off power and unplug any power cords/cables, and
- Reinstall the chassis lid before restoring power.



Important Safety Instructions

Pay close attention to the following safety instructions before performing any of the operation. Basic safety precautions should be followed to protect yourself from harm and the product from damage:

- Operation of the product should be carried out by suitably trained, qualified, and certified personnel only to avoid risk of injury from electrical shock or energy hazard.
- Disconnect the power cord from the wall outlet when installing or removing main system components, such as the motherboard and power supply unit.
- Place the system on a stable and flat surface.
- Use extreme caution when working with high-voltage components.
- When handling parts, use a grounded wrist strap designed to prevent static discharge.
- Keep the area around the system clean and clutter-free.
- Keep all components and printed circuit boards (PCBs) in their antistatic bags when not in use.
- Handle a board by its edges only; do not touch its components, peripheral chips, memory modules or contacts.
- The power cord must be connected to a socket or outlet with a ground connection.

Contents

Chapter 1 Introduction	1
1.1 Shipping Box Contents	2
1.2 Specifications	3
Chapter 2 Server system overview	6
2.1 System Components	6
2.2 Internal Features	7
2.3 System Front Panel	9
2.4 System Rear Panel	10
2.5 Front Control Panel Buttons and LEDs	11
2.6 PSU LED	13
2.7 Drive Tray and LEDs	14
Chapter 3 Hardware installation and maintenance	15
3.1 Server Top Cover	16
3.2 Hard Drive	18
3.3 Hard Drive Backplane Module	21
3.4 Power Supply	22
3.5 System Fan	23
Chapter 4 Server Board (SIENAD8UD3)	24
4.1 Layout	24
4.2 Block Diagram	27
4.3 Installing the CPU (LGA4844 Socket)	28
4.4 Installing the Memory Modules (DIMM)	32
Appendix A	33
Installing the Server in a Rack	33

Chapter 1 Introduction

Thank you for purchasing 2U12L2S-SIENA, a reliable barebone system produced under ASRock Rack's consistently stringent quality control. It delivers excellent performance with robust design conforming to ASRock Rack's commitment to quality and endurance.

This guide provides the instructions of insertion and extraction of chassis components, such as chassis covers, system fans, power supplies, hard disk drive trays, and other main components this system supports. If the system is pre-installed a serverboard, please refer to the user's manual of the serverboard for the information of the serverboard components, specifications and BIOS settings.

System	ASRock Rack Server Board
2U12L2S-SIENA	SIENAD8UD3



Because the hardware specifications might be updated, the content of this documentation will be subject to change without notice.



The illustrations shown in this manual are for reference purposes only and may not exactly match the model purchased.



If requiring technical support related to this system, please visit the website for specific information about the using model.

<http://www.asrockrack.com/support/>

1.1 Shipping Box Contents

Item	Quantity
Server barebone :2U12L2S-SIENA	1
CPU heatsink	1
Rail kit	1
Accessory box - 2 Power cords - 1 Quick installation guide - 2 M2 screws	

*If any items are missing or appear damaged, contact the authorized dealer.*

1.2 Specifications

2U12L2S-SIENA	
System	
Form Factor	2U Rackmount
Dimensions	680 x 430 x 88mm (26.7" x 16.9" x 3.5")
Support MB	SIENAD8UD3
Front Panel	
Buttons	Power button w/ LED, ID button w/ LED, System reset
LEDs	HDD Activity, LAN 1/2, System Event
I/O Ports	1 Type-A (USB3.2 Gen1)
External Drive Bay / Storage	
Front Side Drive Bay	12 Hot-swap 3.5" SATA drive bays
Front Side Backplane	12-port SATA passive backplane
Rear Side	2 Hot-swap 2.5" SATA drive bays, supports 7mm height
Rear Side Backplane	2-port SATA passive backplane
Internal Side	2 M-key (PCIe5.0 x4), supports 22110/2280 form factor
Power Supply	
Type	1+1 CRPS
Output Watts	800W
Efficiency	80-PLUS Platinum/Titanium
AC Input	AC 100-240V~/10.5A, 60/50Hz
System Fan	
Fan	3 PWM Hot-swap 80x38mm fans
Processor System	
CPU	Supports AMD EPYC™ 8004 series processors
Socket	Single Socket SP6 (LGA4844)
Chipset	System on Chip
System Memory	
Supported DIMM Quantity	8 DIMM slots (2DPC/1DPC)
Supported Type	Supports DDR5 288-pin RDIMM

Max. Capacity per DIMM	96GB (2Rx4)
Max. DIMM Frequency	4800MHz
Voltage	1.1V
PCIe Expansion Slots	
PCIe x 16	2 HHHL PCIe5.0 x16
Ethernet	
Additional GbE Controller	Intel® i210: 2 RJ45 (1GbE)
Server Management	
BMC Controller	ASPEED AST2600
IPMI Dedicated GLAN	1 Realtek RTL8211F for dedicated management GLAN
Graphics	
Controller	ASPEED AST2600
VRAM	DDR4 512MB
Rear I/O	
UID Button/ LED	1 UID button w/ LED
VGA Port	1 DB15 (VGA)
USB Port	2 Type-A (USB3.2 Gen1)
RJ45	2 RJ45 (1GbE) 1 dedicated IPMI
System BIOS	
BIOS Type	AMI UEFI BIOS; 256Mb SPI Flash ROM
BIOS Features	ASRock Rack Instant Flash, ACPI 6.4 and above compliance wake up events, SMBIOS 3.5.0 and above, Plug and Play(PnP)
Hardware Monitor	
Temperature	CPU, MB, Card side, TR1 Temperature sensing
Fan	Fan Tachometer
	Quiet Fan (Allow Chassis Fan Speed Auto-Adjust by CPU Temperature)
	Fan Multi-Speed Control
Voltage	VDDCR_CPU, VDDCR_SOC, VDDIO, VDD_18_S5, VDD_33_S5, VDD_11_S3, +3V, +5V, +12V, +BAT, +1V8SB, 3VSB, 5VSB

Environment	
Temperature	Operation temperature: 10°C ~ 35°C
	Non operation temperature: -40°C ~ 70°C
Humidity	Non operation humidity: 20% ~ 90% (Non condensing)

**Please note that the functions are supported depending on the type of the server board.*




Please refer to the user manual of the motherboard for detailed information about motherboard components and features.

Chapter 2 Server system overview


This chapter provides diagrams showing the location of important components of the server system.

2.1 System Components




**The illustrations in this User Manual are for references only. The actual product may be slightly different by SKU.*

2.2 Internal Features




No.	Description
1	Spare Slot Brackets
2	Rear I/O Panel (<i>depends on the specification of the server board</i>)
3	2 Hot-swap 2.5" SATA drive bays
4	1+1 800W CRPS
5	Server board
6	Fan bracket
7	System fan1 (Hot-swappable)
8	System fan2 (Hot-swappable)
9	System fan3 (Hot-swappable)
10	12-port SATA passive backplane (BPB)
11	Front control panel
12	12 Hot-swap 3.5" SATA drive bays
13	Front I/O port (1 USB 3.2 Gen1 port)

2.3 System Front Panel



No.	Description
1	Front control panel and LEDs
2	12 Hot-swap 3.5" SATA drive bays
3	1 USB 3.2 Gen1 port


2.4 System Rear Panel



No.	Description
1	1+1 800W CRPS
2	2 Hot-swap 2.5" SATA drive bays, supports 7mm height
3	Rear vent
4	I/O shield <i>(depends on the specification of the server board)</i>

2.5 Front Control Panel Buttons and LEDs

Front Control Panel



No.	Descriptions	
1		Power button
2		Power status LED
3		Drive activity LED
4		LAN activity LED
5		System alert LED
6		System ID LED
7		System ID button
8		System reset button

**Please note that the functions are supported depending on the type of the server board.*

Power Button

Press the power switch button to toggle the system power on. To remove all power from the system completely, disconnect the power cord from the server.

System ID Button

Press the System ID button to toggle the front panel ID LED and the baseboard ID LED on and off. Use this button to locate the server working on behind a rack of servers.

System Reset Button

When the system is completely unresponsive, press the system reset button to reboot the server without shutting it off and initialize the system.

LED Definitions

Power Status LED	
Status	Description
Blue	Power on
Off	Power off


System ID LED	
Status	Description
Blue	System identification is activated
Off	System identification is disabled

LAN Activity LED	
Status	Description
Blue	Link between system and network
Blinking Blue	Detect LAN Activity
Off	No access

Drive Activity LED	
Status	Description
Blue	HDD is activated
Blinking Blue	Detect or Locate HDD
Off	HDD no connected or power-off


System Alert LED	
Status	Description
Red	System error
Off	Running or normal operation

2.6 PSU LED



PSU Status LED	
Status	Description
Green	Output on and ok
Off	NO AC power to all power supplies
Amber	- AC cord unplugged, or AC power lost; with a second power supply in parallel still with AC input power. - Power supply critical event is causing a shutdown; failure, over current, short circuit, over voltage, fan failure, over temperature
1Hz Blink Amber	Power supply warning events where the power supply continues to operate; high temp, high power, high current, slow fan
1Hz Blink Green	- PSU standby state AC present/Only 12VSB on - Power supply is cold standby state or always standby state as defined in the Cold Redundancy section of the CRPS Common Requirements Specification
2Hz Blink Green	FW updating for power supply

2.7 Drive Tray and LEDs



No.	Description
1	HDD Fault/Status LED
2	HDD Activity LED

LED Definitions

Hard Drive Power LED	
Status	Description
Red	HDD fault or locate HDD
Blinking Red	Re-build status
Off	Normal

Hard Drive Activity LED	
Status	Description
Blue	HDD present
Blinking Blue	Detect or locate HDD activity
Off	HDD no connected or powered-off

Chapter 3 Hardware installation and maintenance

This chapter helps user to assemble the chassis and install components.

Before You Begin

Before working with the server, pay close attention to the “Important Safety Instructions” at the beginning of this manual.

1. Make sure the server is powered off.

Power down the server if it is still running.

- (1) Press the Power button to power off the server from full-power mode to standby-power (sleep) mode. The Power LED at the front turns from solid green to blinking green.
- (2) Disconnect the power cord first from the AC outlet and then from the server.
The power LED turns off.



The server is not completely powered down when you press the Power button on the front panel. The Power button lets the server toggle between Power On and Standby (Sleep) modes. Some internal circuitry remain active in the Standby mode. To remove all power from the system completely, be sure to disconnect the power cord from the server.

2. Ensure having a clean and stable working environment. Avoid dust and dirt because contaminants may cause malfunctions.
3. Ground yourself properly before touching any system component. A discharge of static electricity may damage components. Wear a grounded wrist strap if available.

Installing Procedures

The followings are prerequisite to be installed.

- 3.5" hard drive (s)
- 2.5" hard drive (s)
- Power supply units (Pre-installed)
- System fans (Pre-installed)
- Fan board (Pre-installed)
- Server board (Pre-installed)
- Hard drive backplane boards (Pre-installed)
- Front panel boards (Pre-installed)



1. Some components are already pre-installed. Simply properly connect the required cables before or after installation.
2. Refer to the user manual of the server board for instructions on how to install server board components.


3.1 Server Top Cover

Removing the Top Cover




1. Before removing the top cover, power off the server and unplug the power cord.
2. The system must be operated with all the chassis top cover installed to ensure proper cooling.

1. Press the locking button on both sides of the chassis.
2. Push the top cover toward the REAR side of the chassis.
3. Lift up and remove the top cover.



Installing the Top Cover

1. Lower the top cover on the chassis, making sure the side latches align with the cutouts.
2. Push the top cover toward the FRONT side of the chassis until hearing clicks to secure the top cover with the chassis.




3.2 Hard Drive

The system supports 12 3.5" hot-swappable hard disk bays on the front panel and 2 2.5" hot-swappable hard disk bays on the rear panel .


Removing the 3.5" Hard Drive

1. Press the locking lever latch on the drive tray to unlock the retention lever.
2. Rotate the lever out and away from the bay
3. Pull the tray out of the chassis.
4. Remove the hard drive by pushing the hard drive out from the backside of the tray.




Installing the 3.5" Hard Drive

1. Align the tray's dimples to insert the hard disk into the tray until the side dimples lock into place.
2. Secure the hard disk to the tray with two screws.
3. Insert the tray into the hard drive bay until the drive is fully seated.
4. Push in the locking lever to lock the tray into place.




Removing the 2.5" Hard Drive

1. Press the locking lever latch on the tray to unlock the retention lever.
2. Rotate the lever out and away from the bay and pull the hard drive out of the tray.



Installing the 2.5" Hard Drive



1. Engage two embossed pins into the side dimples on the tray.
2. Carefully push down the other side of the tray until the other two embossed pins and side dimples lock into place.
3. Slide the tray into the hard drive bay until the drive is fully seated.
4. Push in the locking lever to lock the tray into place.



3.3 Hard Drive Backplane Module

Removing the Hard Drive Backplane Module (BPB)

1. Unplug all cables from the backplane module and release the module by shifting the hook.
2. Hold on both sides of the module to lift the module upward.



3.4 Power Supply

The system can accommodate two power supplies in the bay at the rear of the chassis. Each unit provides up to 800Watts of power.

One power supply is required for full load operation, with the other power supply purely as a redundant, load-sharing backup. It can be removed without affecting system operation.




1. Before replacing the power supply, power off the server, unplug the power cord, and disconnect all wiring from the power supply.
2. For the redundant unit installation, it does not need to power down the server.

Replacing the Power Supply Unit

To remove a failed power supply, identify the failed power supply by checking the power supply LED on the PSU.

1. Hold on the power supply handle while pressing the locking lever towards the power supply handle.
2. Pull the power supply out from the chassis.
3. Install a new power supply unit by pushing it into the chassis. Ensure the power supply unit is fully inserted and securely seated on the chassis.




3.5 System Fan

The system supports 3 hot-swappable system fans.

Replacing the System Fan

1. Unplug all the cables around the fan.
2. Lift to remove the failed fan.
3. Align the mounts on the fan with the mounting holes on the fan bracket to insert a new fan into the chassis.
4. Make sure the fan is well seated.




4.1 Layout



No.	Description
1	IPMI LAN LED Header (IPMI_LED1)
2	2 x 288-pin DDR5 DIMM Slots (DDR5_E1, DDR5_H1)
3	2 x 288-pin DDR5 DIMM Slots (DDR5_F1, DDR5_H2)
4	Micro-Fit Power Connector (ATX4PIN1)
5	ATX 12V Power Connector (ATX12V1)
6	ATX 12V Power Connector (ATX12V2)
7	ATX 12V Power Connector (ATX12V3)
8	PWM Configuration Header (PWM_CFG1)
9	Mini Cool Edge IO Connector (PCIe5.0 x8 or 8 SATA 6Gb/s) (MCIO1)
10	Mini Cool Edge IO Connector (PCIe5.0 x8 or 8 SATA 6Gb/s) (MCIO2)
11	2 x 288-pin DDR5 DIMM Slots (DDR5_A1, DDR5_D1)
12	Mini Cool Edge IO Connector (PCIe5.0 x8) (MCIO3)
13	2 x 288-pin DDR5 DIMM Slots (DDR5_B1, DDR5_D2)
14	Mini Cool Edge IO Connector (PCIe5.0 x8) (MCIO4)
15	M.2 Socket (M2_1) (Type 2280 / 22110)
16	Mini Cool Edge IO Connector (PCIe5.0 x8) (MCIO5)
17	M.2 Socket (M2_2) (Type 2280 / 22110)
18	System Fan Connector (FAN4)
19	System Fan Connector (FAN1)
20	System Fan Connector (FAN5)
21	System Fan Connector (FAN2)
22	System Fan Connector (FAN6)
23	System Fan Connector (FAN3)
24	PSU SMBus (PSU_SMB1)
25	SATA Power Connector (SATAPWR1)
26	OCuLink Connector (PCIe3.0 x4) (OCU1)
27	SATA SGPIO Connector (SATA_SGPIO4)
28	System Panel Header (PANEL1)
29	Auxiliary Panel Header (AUX_PANEL1)
30	SATA SGPIO Connector (SATA_SGPIO3)
31	USB 3.2 Gen1 Header (USB3_3_4)
32	Speaker Header (SPEAKER1)
33	Backplane PCI Express Hot-Plug Connector (CPU1_HSBP1)
34	SATA SGPIO Connector (SATA_SGPIO1)

No.	Description
35	SATA SGPIO Connector (SATA_SGPIO2)
36	BUZZER1
37	Intelligent Platform Management Bus header (IPMB1)
38	BMC SMBus Header (BMC_SMB1)
39	COM Port Header (COM1)
40	Non Maskable Interrupt Button (NMI_BTN1)
41	PCI Express 5.0/CXL1.1 x16 Slot (PCIE4)
42	Thermal Sensor Header (TR1)
43	Clear CMOS Pad (CLRMOS1)
44	PCI Express 5.0/CXL1.1 x16 Slot (PCIE6)
45	Mini Cool Edge IO Connector (PCIe5.0 x8 or 8 SATA 6Gb/s) (MCIO6)
46	Mini Cool Edge IO Connector (PCIe5.0 x8 or 8 SATA 6Gb/s) (MCIO7)
47	SPI TPM Header (TPM_BIOS_PH1)
48	AMD Socket SP6 (LGA4844) (CPU1)

4.2 Block Diagram





Each P* lane can support CX11.1 type3, but the lane must set equal width, ex. 1 x16, 2 x8, 4 x4 .


4.3 Installing the CPU (LGA4844 Socket)




1. Before inserting the CPU into the socket, please check if the PnP cap is on the socket, if the CPU surface is unclean, or if there are any bent pins in the socket. Do not force to insert the CPU into the socket if above situation is found. Otherwise, the CPU will be seriously damaged.
2. Unplug all power cables before installing the CPU.




3



4



5




Please make sure that the carrier frame with CPU is closely attached to the rail frame while inserting it.




Install the carrier frame with CPU. Don't separate them.


6



7



8




4.4 Installing the Memory Modules (DIMM)




The DIMM only fits in one correct orientation. It will cause permanent damage to the motherboard and the DIMM if forcing the DIMM into the slot at incorrect orientation. For more information about DIMM installation, please refer to the User Manual that comes with the server board used.


1



2



3



Appendix A


Installing the Server in a Rack

This section describes how to rackmount the 2U12L2S-SIENA server with slide rail assembly.




The rails installation instructions in this manual are example only, the actual rail assembly procedure may differ slightly.

The rail assembly consists of outer, middle and inner rail.




Some slide rails are labeled with either L or R, please identify prior to rail installation. Install the rail labeled with L on the left side of rack, and the rail labeled with R on the right side.


1. Release and detach the inner rail from the slide.




2. Attach inner rail to the system.




3. Attach outer rail to the rack.



4. (1) Caution! Verify ball bearing retainer is locked forward.
(2) Pull out the middle rail until locked out.



5. Slide release tab and push system into rack.



Contact Information

Contact ASRock Rack or want to know more about ASRock Rack, you're welcome to visit ASRock Rack's website at <http://www.asrockrack.com>; or contact the dealer for further information. For technical questions, please submit a support request form at <https://event.asrockrack.com/tsd.asp>

ASRock Rack Incorporation

e-mail: ASRockRack_sales@asrockrack.com

ASRock Rack EUROPE B.V.

Bijsterhuizen 11-11
6546 AR Nijmegen
The Netherlands
Phone: +31-24-345-44-33

ASRock Rack America, Inc.

13848 Magnolia Ave, Chino, CA91710 U.S.A.
Phone: +1-909-590-8308
Fax: +1-909-590-1026