



— Industrial —

IMB-195 CPU Support List

Socket	Family	Number	Core	Frequency	Cache	Power	Since BIOS
1151	Core i7	i7-7700K(B0)	Kaby Lake	4.2GHz	8MB	91W	P1.30
1151	Core i7	i7-7700(B0)	Kaby Lake	3.6GHz	8MB	65W	P1.30
1151	Core i7	i7-7700T(B0)	Kaby Lake	2.9GHz	8MB	35W	P1.30
1151	Core i7	i7-6700K(R0)	Skylake S	4.0GHz	8MB	91W	All
1151	Core i7	i7-6700(R0)	Skylake S	3.4GHz	8MB	65W	All
1151	Core i7	i7-6700T(R0)	Skylake S	2.8GHz	8MB	35W	All
1151	Core i5	i5-7600K(B0)	Kaby Lake	3.8GHz	6MB	91W	P1.30
1151	Core i5	i5-7600(B0)	Kaby Lake	3.5GHz	6MB	65W	P1.30
1151	Core i5	i5-7600T(B0)	Kaby Lake	2.8GHz	6MB	35W	P1.30
1151	Core i5	i5-7500(B0)	Kaby Lake	3.4GHz	6MB	65W	P1.30
1151	Core i5	i5-7500T(B0)	Kaby Lake	2.7GHz	6MB	35W	P1.30
1151	Core i5	i5-7400(B0)	Kaby Lake	3.0GHz	6MB	65W	P1.30
1151	Core i5	i5-7400T(B0)	Kaby Lake	2.4GHz	6MB	35W	P1.30
1151	Core i5	i5-6600K(R0)	Skylake S	3.5GHz	6MB	91W	All
1151	Core i5	i5-6600(R0)	Skylake S	3.3GHz	6MB	65W	All
1151	Core i5	i5-6600T(R0)	Skylake S	2.7GHz	6MB	35W	All
1151	Core i5	i5-6500(R0)	Skylake S	3.2GHz	6MB	65W	All
1151	Core i5	i5-6500T(R0)	Skylake S	2.5GHz	6MB	35W	All
1151	Core i5	i5-6402P (R0)	Skylake S	2.8GHz	6MB	65W	All
1151	Core i5	i5-6400(R0)	Skylake S	2.7GHz	6MB	65W	All
1151	Core i5	i5-6400T(R0)	Skylake S	2.2GHz	6MB	35W	All
1151	Core i3	i3-7350K(S0)	Kaby Lake	4.2GHz	4MB	60W	P1.30
1151	Core i3	i3-7320(S0)	Kaby Lake	4.1GHz	4MB	51W	P1.30
1151	Core i3	i3-7300(S0)	Kaby Lake	4.0GHz	4MB	51W	P1.30
1151	Core i3	i3-7300T(S0)	Kaby Lake	3.5GHz	4MB	35W	P1.30
1151	Core i3	i3-7100(S0)	Kaby Lake	3.9GHz	3MB	51W	P1.30
1151	Core i3	i3-7100T(S0)	Kaby Lake	3.4GHz	3MB	35W	P1.30
1151	Core i3	i3-6320(S0)	Skylake S	3.9GHz	4MB	51W	All
1151	Core i3	i3-6300(S0)	Skylake S	3.8GHz	4MB	51W	All
1151	Core i3	i3-6300T(S0)	Skylake S	3.3GHz	4MB	35W	All
1151	Core i3	i3-6100(S0)	Skylake S	3.7GHz	3MB	51W	All
1151	Core i3	i3-6100T(S0)	Skylake S	3.2GHz	3MB	35W	All
1151	Core i3	i3-6098P (R0)	Skylake S	3.6GHz	3MB	54W	All
1151	Pentium	G4600T(S0)	Kaby Lake	3.0GHz	3MB	35W	P1.30
1151	Pentium	G4560(B0)	Kaby Lake	3.5GHz	3MB	54W	P1.30
1151	Pentium	G4560T(S0)	Kaby Lake	2.9GHz	3MB	35W	P1.30
1151	Pentium	G4620(S0)	Kaby Lake	3.7GHz	3MB	51W	P1.30
1151	Pentium	G4600(S0)	Kaby Lake	3.6GHz	3MB	51W	P1.30
1151	Pentium	G4520(S0)	Skylake S	3.6GHz	3MB	47W	All
1151	Pentium	G4500(S0)	Skylake S	3.5GHz	3MB	47W	All
1151	Pentium	G4500T(S0)	Skylake S	3.0GHz	3MB	35W	All
1151	Pentium	G4400(S0)	Skylake S	3.3GHz	3MB	47W	All
1151	Pentium	G4400T(S0)	Skylake S	2.9GHz	3MB	35W	All

1151	Celeron	G3950(S0)	Kaby Lake	3.0GHz	2MB	51W	P1.30
1151	Celeron	G3930(S0)	Kaby Lake	2.9GHz	2MB	51W	P1.30
1151	Celeron	G3930T(S0)	Kaby Lake	2.7GHz	2MB	35W	P1.30
1151	Celeron	G3920(S0)	Skylake S	2.9GHz	2MB	47W	All
1151	Celeron	G3900(S0)	Skylake S	2.8GHz	2MB	47W	All
1151	Celeron	G3900T(S0)	Skylake S	2.6GHz	2MB	35W	All